

STEC SMALL CARDS WEAR LEVELING AND LIFETIME CALCULATOR

INTRODUCTION

STEC Small Card family includes Secure Digital, miniSD, microSD, MMCPlus and SD High Capacity. To build high quality and durable Industrial Grade Small Cards, STEC only uses Single Level Cell (SLC) Flash for its superior endurance, performance and reliability

In fact, STEC considers that Multi Level Cell (MLC) technology is not yet mature to be used in quality-demanding applications for the following reasons:

- Limited number of program/erase cycles per physical block: MLC flash is rated maximum 10,000 program/erase operations per physical block (with 4bit error correction) while SLC flash can perform 100,000 cycles (with 1 bit Error Correction).
- Slower speed operations: MLC is 4 times slower than SLC in program and 2 times slower in random access
- MLC Higher write and erase complexity increases the probability of bit fail

To enhance the Program/Erase operations of SLC flash, STEC Small Cards implement a powerful hardware Error Detection and Error Correction Code and a File System that translates the physical structure of the memory (pages and blocks) to operate on logical structure (cluster, sector and management units). The main component of STEC File System is the Dynamic Wear Leveling. The purpose of Wear Leveling is to ensure even distribution of Program/Erase cycles so that each block ages at the same rate.

The combination of the Wear Leveling and the powerful Error Correction Code enables the specification of the cards at 2,000,000 program/erase cycles for each logical block.

WEAR LEVELING

The minimum read and write operation unit inside a NAND flash chip is called a "PAGE." Several pages form a Block that is the minimum erase operation unit. STEC Industrial Grade Small Cards group NAND flash blocks into several management units of 128MB (64MB for 64MB card). Wear leveling is implemented within a management unit. The reason of using management unit of 128MB instead of the full memory capacity is to be able to perform extensive wear leveling without jeopardizing the performance of the card.

The table below summarizes the page size, block size, number of pages per block and number of blocks per device:

	64MB	128MB	256MB	512MB	1GB	2GB
Page size	528Bytes	2Kbytes				
Block size	16Kbytes	128Kbytes				
# of Pages per Block	32 Pages	64 Pages				
# of Block per device	4096	1024	2048	4096	8192	16384

# of Management unit	1	1	2	4	8	16
----------------------	---	---	---	---	---	----

When the host gives a write command to the card, the data is written into an empty physical block. Each block has a counter, and the wear leveling software makes sure that only the youngest block within a management unit is used for a new write operation.

The result is the rotation of the whole physical blocks within the management unit. Apart from blocks used to store static data, all the other blocks within a management unit are used for wear leveling operation. Static files (files that are not often updated) reduce the number of spare blocks available for wear leveling.

There are alternative solutions on the market that also use the blocks occupied by static files for wear leveling. As such, the number of blocks available for wear leveling might be higher. On the other hand, moving static data adds stress to the cell array because non-required write and erase operations are performed in back-ground by the controller. As a consequence, there are more chances to generate bit-flip errors and the performance of the card is significantly impacted.

When only one block is left empty, the write operation cannot be performed as the wear leveling cannot be executed and thus the firmware rejects the operation. Read and Erase operations are still available.

LIFETIME CALCULATOR

The lifetime of a STEC Small Card can be calculated as following:

$$\text{Lifetime} = 2\text{Million} \times (C - C_s - 1B) / [\max(\text{block size}, F_s) \times F_r]$$

“C” is the capacity of the card

“Cs” is the Capacity used for static files

“1B” is one block (in fact, if only 1 block is empty, the write operation is not allowed)

“Block size” is 16Kbytes for 64MB card or 128Kbytes for 128MB and higher capacity cards.

“Fs” is the average File Size

“Fr” is the average frequency of file updating

Application Example:

Example #1

An application uses a 512MB SD card. 100MB of the card are used to store static data (i.e. the operating system). The rest of the card is used for updating 10 times per day a file of 50MB.

The lifetime can be calculated as following:

$$\text{Lifetime} = 2,000,000 \times (512\text{MB} - 100\text{MB} - 128\text{KB}) / (50\text{MB} \times 10/\text{day}) = 4,513 \text{ years}$$

Example #2

An application uses a 64MB SD card. 50MB are used to store static data and the rest of the card is used for updating a file of 16KB 5000 times per day.

The lifetime can be calculated as following:

$$\text{Lifetime} = 2,000,000 \times (64\text{MB} - 50\text{MB} - 16\text{KB}) / (16\text{KB} \times 5000/\text{day}) = 980 \text{ years}$$



IF YOU HAVE ANY QUESTIONS PLEASE CONTACT YOUR LOCAL STEC FIELD APPLICATIONS ENGINEER OR SEND A MESSAGE TO OEMSUPPORT@STEC-INC.COM

DOCUMENT CONTROL

Filled out by Author		
Author Name	Davide Villa	
Document Name	STEC SMALL CARDS WEAR LEVELING AND LIFETIME CALCULATOR	
Date of Creation	3/13/2007	
Revision History	Date	Description
	1/2/2007	First release
Filled out By Document Control		
Application note No.	AN-0702	
Document No.		
Distribution Restrictions		With NDA Only
		Upon Approval by Marketing
		Distribute through Sales Only
	X	Available to General Public

STEC Inc. reserves the right to make changes to specifications and product descriptions such as, but not limited to, numbers, parameters and other technical information contained herein without notice. Contact STEC Inc. sales office to obtain the latest specification. All information in this document is provided "as is". STEC Inc. grants no warranty of any kind with respect to this document, either expressed or implied, including, but not limited to any direct, indirect, special, consequential, or incidental damages. Under no circumstances, including but not limited to negligence, shall STEC be liable for damages resulting from reliance on the information present in this document. Some States do not grant the exclusion of limitation of liability and as such this statement may not apply to you. The provisions of this datasheet do not convey to the purchaser of the device any license under any patent rights or other intellectual property rights of STEC Inc. or others. STEC prohibits the recipient of this information from the publication, transmission, or distribution of the information to any third party except as expressly permitted by STEC. STEC products are not authorized for use as critical component in life support devices or systems without express written approval of STEC, Inc.

The information provided may be subject to United States Export Controls. Such information should not be downloaded or exported (i). into (or to a national or resident of) Cuba, Iraq, Libya, North Korea, Iran, Syria, or any other country to which the United States has embargoed goods; or given to (ii). anyone on the United States Treasury Department's list of Specially Designated Nationals or the U.S. Commerce Department's Table of Deny Orders. By using the information, you represent and warrant that you are not located in, under the control of, or a national or resident of any such country or on any such list.

STEC®, Inc., reserves the right to change products or specifications without notice. ©2007 STEC®, Inc. All rights reserved.

Worldwide Headquarters
3001 Daimler Street
Santa Ana, California
92705 USA
Tel: (949) 476-1180
Fax: (949) 476-1209
www.stec-inc.com

STEC Europe
Donau-City-Strasse 1
1220 Vienna, Austria
Tel: +43 1 263 38 08
Fax: +43 1 263 37 65
www.stec-inc.com

STEC Hong Kong
Unit 01-02, 10/F
88 Hing Fat Street
Causeway Bay,
Hong Kong
Tel: +852-3150-8398
Fax: +852-3150-8399
www.stec-inc.com

STEC Japan
Landmark Tower
20/F 2-2-1, Minato-Mirai,
Nishi-ku
YOKOHAMA, 220-8120,
Japan
Tel: +81(0) 45-670-7030
Fax: +81(0) 45-670-7001
www.stec-inc.com

STEC Taiwan
4F, No. 3, Lane 91,
Dongmei Road
Hsinchu City Taiwan
Tel: +886-3-5733233
Fax: +886-3-5733633
www.stec-inc.com